
## KEMET Part Number: T495A685M006ZTE1K8 Obsolete



B450, Tantalum, MnO2 Tantalum, 6.8 uF, 20%, 6.3 V, SMD, Molded, Low ESR, Surge Robust, 1.8 Ohms, 3216, Height Max = 1.8mm



| General Information |  |
|---------------------|--|
| Supplier:           | KEMET  |
| Series:             | B450   |
| Dielectric:         | MnO2 Tantalum  |
| Style:              | SMD Chip   |
| Description:        | SMD, Molded, Low ESR, Surge<br>Robust                          |
| Features:           | Low ESR, Surge Robust  |
| RoHS:               | Yes  |
| Termination:        | Tin  |
| Notes:              | Obsolete. Old part<br>number [Obsolete] was<br>B45006A6859M188 |
|                     | _ =  |

Conoral Information

| Dimensions |                |
|------------|----------------|
| Footprint  | 3216           |
| L          | 3.2mm +/-0.2mm |
| W          | 1.6mm +/-0.2mm |
| Н          | 1.6mm +/-0.2mm |
| S          | 0.8mm +/-0.3mm |
| F          | 1.2mm +/-0.1mm |
| K          | 1.3mm TYP      |

| Packaging Specifications |            |
|--------------------------|------------|
| Packaging:               | T&R, 178mm |
| Packaging Quantity:      | 2000       |

| Specifications         |   |
|------------------------|---|
| Capacitance:           | 6.8 uF  |
| Capacitance Tolerance: | 20%   |
| Voltage DC:            | 6.3 VDC (85C), 4.22 VDC (125C)                    |
| Temperature Range:     | -55/+125C   |
| Rated Temperature:     | 85C   |
| Dissipation Factor:    | 6%  |
| Failure Rate:          | N/A   |
| Resistance:            | 1.8 Ohms (100kHz)                                 |
| Current:               | 200 mAmps (25C), 180 mAmps (85C), 80 mAmps (125C) |
| Leakage Current:       | 0.5 uA  |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.



© 2006 - 2018 IntelliData.net